

ADR	HEXADR	NAME	Description	shadow	OS
16	\$10	POKMSK	Interrupt-Maske für POKEY	<a href="#">IRQEN</a>	

BIT	DECIMAL	FUNCTION
7	128	BREAK key is enabled.
6	64	"other key" interrupt is enabled.
5	32	Serial input data ready interrupt is enabled.
4	16	Serial output data required interrupt is enabled.
3	8	Serial out transmission finished interrupt is enabled.
2	4	POKEY timer four interrupt is enabled (only in the "B" or later versions of the OS ROMs).
1	2	POKEY timer two interrupt is enabled.
0	1	POKEY timer one interrupt is enabled.